

CONDENSED CROSS-REFERENCE

This cross covers most popular fuses for which there is a similar Littelfuse standard item. Furnished for your convenience, it is meant to serve as a guide only for product selection. We suggest you check all applicable specifications before making substitutions. For special applications, consult the factory.

For more complete information, and for fuse block and medium voltage fuse cross referencing, request Cross Reference Booklet EC501, computer cross reference disk PF960, call (800)TEC-FUSE (800-832-3873), or visit our website at www.littelfuse.com

Competition	Littelfuse	Competition	Littelfuse	Competition	Littelfuse	Competition	Littelfuse
10KOTN	NLN	CSF13X	L15S	KLMR	CCMR	SA	SAO
10KOTS	NLS	CSF25X	L25S	KLU	KLLU or KLPC	SBS	BLS
50KOTN	NLN	CSF50P	L50S	KON	NLN	SC	SLC
50KOTS	NLS	CSF60C	KLC (AC only)	KOS	NLS	SCLR	KLSR
A013F	L15S	CSF60X	L60S (AC only)	KRPC (SP)	KLPC		
A015F	L15S	CSF70P	L70S			SEC	SLC
A015R	L15S	CTN-R	KLNR	KRPC-L	KLPC	SF13X	L15S
A025F	L25S			KTK	KLK	SF25X	L25S
A050F	L50S	CTS-R	KLSR	KTKR	KLKR	SF50P	L50S
A060F	L60S	DMM	FLU	KTNR	KLNR	SF60C	KLC
		EBS	BLS	KTO	KLO	SF60X	L60S
A060URL	KLK	ECK	CCK	KTSR	KLSR	SF70P	L70S
A070F	L70S	ECNR	FLNR_ID ⁴	KTU	KLPC	SFE	307 (SFE)
A13X	L15S	ECSR	FLSR_ID	LCL	KLPC or KLLU	SL	SLO
A25X	L25S	EDCC	CCMR			T	TOO
A2D-R	LLNRK	ELN	LKN	LCU	KLPC or KLLU		
A2K-R	KLNR	ELS	LKS			TJN	JLLN
A3T	JLLN	ERN	RLN	LENRK	LLNRK	TJS	JLLS
A4BQ	KLPC					TL	TLO
A4BT	KLLU or KLPC	ERS	RLS	LESRK	LLSRK_ID	TPS	TLS
A4BY	KLPC or KLLU	FNA	FLA	LKN	LKN	TR	FLNR_ID
A4J	JLS	FNB	235	LKS	LKS	TRM	FLM
A50P	L50S	FNM	FLM	LKU	KLLU	TRN-R	FLNR_ID
A60X	L60S	FNQ	FLQ	LONRK	LLNRK	TRS	FLSR_ID
A6D-R	LLSRK_ID	FNQ-R	KLDR	LOSrk	LLSRK_ID	TRS-R	FLSR_ID
A6K-R	KLSR	FRN-R	FLNR_ID ⁴	LPCC	CCMR	XL25X	L25S
A6T	JLLS	FRS-R	FLSR_ID	LPJ (SP)	JTD_ID		
A70P (10-30A Type 1)	L70S	FWA	L15S ³	LPNRK (SP)	LLNRK	XL50F	L50S ²
A70P (35-800A Type 4)	L70S	FWH	L50S ³	LPSRK (SP)	LLSRK_ID	XL60C	KLC ²
ACK	CCK					XL70F	L70S ²
AG	SLC	FWP	L70S ²	MCL	KLK		
		FWX	L25S ²	MCR	251		
AGA	301	GDA	216	MDA	326	1	Use #30707.5 to replace AGW 7.5 amp.
AGC	312	GDB	217	MDL	313		
AGU (1-30A)	BLN	GDC	218	MDQ	313		
AGV	303 ¹	GDL	313	MDX	313	2	Check specific mounting dimensions before substituting.
AGX (1/500-1/10A)	361	GEB	LEB	MEN	FLM		
AGX (1/8-30A)	362	GEBN	LET	MEQ	FLQ	3	Check fuse characteristics and mounting dimensions for specific application before substituting.
AJT	JTD_ID	GFA	251	MID	FLA		
ANL	CNL	GFN	FLA	MOF	BLN	4	For 1/10—30A order non-indicating FLNR series fuses.
ANN	CNN						
ATC	ATO	GGC	312	MOL	BLF		
		GGM	235	MRL	L15S		
ATDR	CCMR	GGX (1/500-1/10A)	361	MTH	312		
ATM	KLK	GGX (1/8-30A)	362	NCLR	KLNR		
ATMR	KLKR	GLR	LGR	NON	NLN		
ATQ	FLQ	GMA	235	NOS	NLS		
ATQR	KLDR	GMD	239	NRN	NLN		
AX	481	GMF	LMF	NRN (15-60A)	NLKP		
BAF	BLF	GMT	481	NRS	NLS		
BAN	BLN	HCLR	KLKR	OT	NLN		
BBS	BLS						
CCK	CCK	HCTR	KLDR	OTM	BLF or BLN		
		HEB	LEB	OTN	NLN		
		HET	LET	OTS	NLS		
CGL (2-100A)	2CO	HLR	LHR	REN	RLN		
CGL (125-600A)	2CC	JDL	JTD_ID	RES	RLS		
CJS	JLS	JFL	JLS	RFA	L15S		
CLF	KLPC or KLLU	JHC	JTD_ID	RFC	KLC		
CLL	KLLU or KLPC	JJN	JLLN	RFL (750V)	L70S (700V)		
CLU	KLLU or KLPC	JJS	JLLS	RFN (Gould)	RLN		
CMF	BLN	JKS	JLS	RFS (Gould)	RLS		
CNL	CNL			RFV	L50S		
CNM	FLM	KAA	L15S	RHN	KLNR		
CNN	CNN	KAB	L25S	RHS	KLSR		
CNQ	FLQ	KAC	KLC	RLN (Gould)	LKN		
CRN-R	FLNR_ID ⁴	KBH	L50S	RLS (Gould)	LKS		
		KLM	KLKD	S	SOO		
CRS-R	FLSR_ID						



Expertise Applied | Answers Delivered